



THALIA LE-B QUICK START MENU

START

PRESS THE [OK] BUTTON ONCE TO ENTER THE QUICK START MENU.

STEP 1...

THE SCREEN WILL DISPLAY "LANG" (LANGUAGE)...

...2...

...PRESS THE [-] BUTTON TO SCROLL DOWN TO "ENG" (ENGLISH) AND THEN PRESS [OK]

...3...

NEXT YOU SELECT THE TYPE OF MOTOR...

...4...

PRESS THE [-] BUTTON TO SCROLL DOWN...

- ELI 250 BT... ELI
- PHOBOS BT... PHOb
- IGEA BT... IGER
- LUX BT... LUH
- LUX G BT... LUHG
- SUB BT... SUB

...AND THEN PRESS THE [OK] BUTTON ONCE YOU HAVE SELECTED YOUR OPERATOR

...5...

THEN SELECT THE NUMBER OF MOTORS CONNECTED...

...6...

"1" OR "2" AND PRESS [OK]

...7...

NEXT, DETERMINE THE OPENING DIRECTION...

...8...

SELECT "INT" FOR PULL-TO-OPEN, OR, "EXT" FOR PUSH-TO-OPEN. THEN PRESS [OK]

...9...

THE SCREEN WILL THEN DISPLAY "PRESET"...

...10...

SCROLL DOWN USING THE [-] BUTTON AND SELECT YOUR PRESET, "AR", "SR", "AC", "SC" OR "IND" BASED ON THE LOGIC FEATURES ON THE TABLE BELOW.

| LOGIC PRESETS | AR | SR | AC | SC | IND |
|----------------------------|-----------------------|----------------------------|----------------------|---------------------------|------------|
| | AUTOMATIC RESIDENTIAL | SEMI-AUTOMATIC RESIDENTIAL | AUTOMATIC COMMERCIAL | SEMI-AUTOMATIC COMMERCIAL | INDUSTRIAL |
| AUTOMATIC CLOSING TIMER | X | | X | | |
| PRE-ALARM | | | X | X | |
| UNINTERRUPTED OPEN CYCLE | | | X | X | |
| INSTANT REVERSE ON CLOSING | X | | X | | |
| HOLD TO RUN | | | | | X |
| QUICK REMOTE PROGRAMMING | X | X | X | X | |

...THEN PRESS [OK].

...12...

THE SCREEN WILL THEN READ "LSW ADJUST" IF LUX OR LUX G WAS SELECTED.

...13...

"OPM1" (OPEN MOTOR 1) WILL BE DISPLAYED ON THE SCREEN

PRESS THE [+] BUTTON UNTIL THE GATE HAS REACHED IT OPEN LIMIT.

...14...

...THEN PRESS [OK] TO SET THE LIMIT.

IF "ERSW" IS DISPLAYED, YOU HAVE EXCEEDED THE OPERATOR LIMIT.

...15...

IF 2 MOTORS WERE SELECTED, "OPM2" WILL SHOW. PRESS [+] TO BRING THE 2ND GATE TO THE FULLY OPEN POSITION...

PRESS [OK] TO SET LIMIT

...16...

IF 2 MOTORS WERE SELECTED, "CLM2" (CLOSE MOTOR 2) WILL SHOW. PRESS THE [-] BUTTON TO CLOSE THE GATE.

PRESS [OK] TO SET LIMIT

...17...

"CLM1" (CLOSE MOTOR 1) IS DISPLAYED. PRESS THE [-] BUTTON TO BRING THE GATE TO IT'S FULLY CLOSED POSITION

PRESS [OK] TO SET LIMIT

...18...

THE SCREEN WILL READ "OK" . PRESS [OK] TO CONTINUE..

...19...

THE WORD "AUTOSET" WILL SCROLL ACROSS THE SCREEN

...20...

UPON PRESSING [OK], THE GATE WILL OPEN AND CLOSE AUTOMATICALLY 1 TO 3 TIMES

WARNING!

...21...

NEXT, THE SCREEN WILL THEN READ "MEM REMOTES"

...22...

WHEN THE SCREEN READS "HIDDEN BUTTON"...

...23...

SIMULTANEOUSLY PRESS AND HOLD THE 2 BUTTONS ON YOUR REMOTE UNTIL THE SCREEN READS "RELEASE"

...24...

THE SCREEN WILL THEN READ "DESIRED BUTTON". PRESS THE BUTTON YOU WANT TO OPERATE THE GATE WITH

...25...

THE SCREEN WILL DISPLAY "OK" AND THE NUMBER OF THE REMOTE IN MEMORY. REPEAT THE PROCESS FOR ADDITIONAL REMOTES

...26...

PRESS [OK] TO FINISH SETUP

YOU'RE DONE!!!

For additional information please refer to the installation manual

Technical Assistance 561-995-8155
U.S.A Toll free: 877-995-8155